

## **TIME CHANGE INSTRUCTIONS**

### **NEAX 1000 / 1400 / 2000 IVS / 2000 IVS-2 / 2000 IPS With Dterm Series III, Series E and Series i Phones**

CAT Mode Procedure: This is to be done while the phone is in an idle state.

1. Press <TRANSFER>
2. Press <CONF>
3. Press \*
4. Press <TRANSFER>
5. Press <CONF>
6. Press #
7. "CAT MODE" displayed on LCD
8. Press <REDIAL or LNR/SPD>
9. "COMMAND" displayed on LCD
10. Press 02
11. Press <RECALL>
12. Press 2
13. Press <RECALL>
14. "02>2>Current Time" displayed on LCD
15. Input correct time using military time (HH MM SS)
16. Press <CONF>

\*\*\*\*\*

### **NEAX 1000 / 1400 / 2000 IVS / 2000 IVS-2 / 2000 IPS With Dterm Series II Phones**

CAT Mode Procedure: This is to be done while the phone is in an idle state.

1. Press <TRANSFER>
2. Press <HOLD>
3. Press \*
4. Press <TRANSFER>
5. Press <HOLD>
6. Press #
7. "CAT MODE" displayed on LCD
8. Press <SPEAKER>
9. "COMMAND" displayed on LCD
10. Press 02
11. Press <ANSWER>
12. Press 2
13. Press <ANSWER>
14. "02>2>Current Time" displayed on LCD
15. Input correct time using military time (HH MM SS)
16. Press <HOLD>